

MODEL	MSRP(\$)	YEAR	OPT HEAD	RF AMP	SERVO	CPU	DRIVER	DSP	D. FILTER	DAC	DAC info (Sony/Vintage)	AUDIO AMP	HP output (per sv)
SONY													
D-5/D-50		1984	KSS110-I	CXA20109	CXA20108	MB88541	MB3876	CX23035		CX20133	16-bit linear, NO oversmpl; Brick	NJM4560	10mWx2, 32Ohm
D-50mkII/D-7/D-77	300(batt+45)	1985	KSS110-II	CXA20108	CXA1023	CXP5024	CXA1083	CX23035		PCM55	16-bit linear	NJM4556	30mWx2, 32Ohm
D-700/D-170 (ac only)		1985	KSS110	CX20109	CX20108	CXP5034		CX23035		CX20133	16-bit linear	NJM4560	10mWx2, 32Ohm
CDP-7F (ac only)		1985	KSS121A	CX20109	CX20108			CX23035		CX20133	16-bit linear	NJM4560	10mWx2, 32Ohm
CDP-S37/S-207 (ac only)		1989	KSS-211A	CXA1081	CXA1082	MSC6458	CXA1291	CXD1125	CXD2550	CXD1161	4xOversampling Dual DAC	M5204P	11mWx2, 32Ohm
D-10/D-100	300(w/batt)	1986	KSS162	CXA1081	CXA1082	CXP5086	CXA1083	CXD1125	SM5806S	PCM55	16-bit linear	NJM4560	30mWx2, 32Ohm
D-3/D-30		1987	KSS162	CXA1081	CXA1082	UPD7503	CXA1083	CXD1125		CXD1140		M5216	15mWx2, 32Ohm
D-160/600		1988		CXA1081	CXA1082	CXP5024		CXD1130		LC7880	DAC w/D.Filter	M5216x2	
D-15/D-150	350	1988	KSS165	CXA1271	CXA1272	CXP5086	MPC1715	CXD1135		PCM60	16-bit linear	M51568	9mWx2, 32Ohm
D-2/D-20	320	1988	KSS162	CXA1271	CXA1272	CXP5024	MPC1715	CXD1130		CXD1161	16-bit linear, 2fs digital filter	M51568	9mWx2, 32Ohm
D-4/D-40	320	1988	KSS162	CXA1271	CXA1272	CXP5024	MPC1715	CXD1130		CXD1161	16-bit linear, 2fs digital filter	M51568	9mWx2, 32Ohm
D-88	360	1988	KSS167	CXA1271	CXA1272	CXP5024	MPC1715	CXD1135		CXD1161	16-bit linear, 2fs digital filter	M51568	9mWx2, 32Ohm
D-25/D-250	360	1989	KSS165/221	CXA1271	CXA1272	CXP5086	MPC1715	CXD1125	CXD1316	PCM66	16-bit linear, 4fs digital filter	M51568	9mWx2, 32Ohm
D-35/D-350	400	1989	SF89	CXA1271	CXA1272	CXP5078	MPC1715	CXD1125	CXD2551	uPD6376	16-bit linear, 8fs digital filter	BA3570(w/DBB)	9mWx2, 16Ohm
D-555/D-2555	500	1989	KSS167	CXA1271	CXA1272	CXP5086	MPC1715	CXD1125+CXD	CXD2550	PCM66 x2	16-bit linear, 8fs digital filter	CXA1263+NJM2107	9mWx2, 32Ohm
D-800K/D-180K	270	1989	KSS220A							CXD1161	16-bit linear, 2fs digital filter	M51568+NJM4560	9mWx2, 32Ohm
D-9/D-90	250	1989	KSS162//220	CXA1271	CXA1272	CXP5086	MPC1715	CXD1247		CXD1161	16-bit linear, 2fs digital filter	M51568+CXA1249(DBB)	9mWx2, 32Ohm
D-99		1990	KSS220	CXA1271	CXA1272	CXP5086	MPC1715	CXD1167		CXD8178	1-bit quartz time-axis control	BA3570(w/DBB)	5mWx2, 16Ohm
D-303v12		1990	SF89	CXA1271	CXA1272	CXP5078	MPC1716	CXD2500		CXD8178	1-bit quartz time-axis control	BA3570(w/DBB)	5mWx2, 16Ohm
D-303v14		1990	SF89	CXA1271	CXA1272	CXP5078	MPC1716	CXD2500	SM5840	SM5871	1-bit quartz time-axis control	BA3570(w/DBB)	5mWx2, 16Ohm
D-66	250	1990	SF89	CXA1271	CXA1272	CXP5086	MPC1715	CXD1125		uPD6376	DUAL DAC, 16-bit linear, 8fs dig	BA3570(w/DBB)	5mWx2, 16Ohm
D-11/12/22		1990	KSS220	CXA1271	CXA1272	CXP5024	MPC1715	CXD1130/1245		CXD1161	16-bit linear, 2fs digital filter	NJM4560+BA3570(asDBB)	9mWx2, 32Ohm
D-202		1991	KSS330	CXA1271	CXA1272	CXP5086	MPC1716	CXD2500		uPD6376	16-bit linear, 8fs digital filter	BA3570(w/DBB)	5mWx2, 16Ohm
D-33		1991	KSS220	CXA1271	CXA1272	CXP5084	MPC1715	CXD1130	SM5840	uPD6376	16-bit linear, 8fs digital filter	BA3570(w/DBB)	5mWx2, 16Ohm
D-802K		1991	KSS220	CXA1271	CXA1602	CXP5084	MPC1715	CXD1167	SM5840	uPD6376	16-bit linear, 8fs digital filter	BA3570(w/DBB)	9mWx2, 16Ohm
D-808K		1991	KSS330	CXA1271	CXA1272	CXP5078	MPC1716	CXD2500	SM5840	PCM67	1-bit DAC	BA3570(w/DBB)	9mWx2, 16Ohm
D-J50		1991	KSS230	HA12156	CXA1272	S1400	MPC1716	CXD1167		PCM66	16-bit linear, 4fs digital filter	BA3558	5mWx2, 16Ohm
D-101		1991	KSS330	CXA1271	CXA1272	CXP5086	MPC1716	CXD2500		uPD6376	16-bit linear, 8fs digital filter	BA3570(w/DBB)	
D-211		1992	KSS330	CXA1271	CXA1602	UPD75328	MPC1716	CXD2500		SM5870		LA4534	9mWx2, 16Ohm
D-311		1992	KSS350	CXA1271	CXA1602	CXP5078	MPC1716	CXD2500		SM5870		LA4534	9mWx2, 16Ohm
D-515		1992	SF89	CXA1271	CXA1272	CXP50712	MPC1716	CXD2500		SM5870		LA4534	4mWx2, 16Ohm
D-34/36		1992	KSS220A	HA12168	HA12168	HD404818	MPC1715	HD49220	HD49220	HD49220	1-bit DAC	NJM2100x2+BA3570(w/DBB)	
D-822		1993	KSS331								1-bit DAC		
D121		1993	KSS331	CXA1672		CXP83412	SC11280	CXD2517		TC9276		LA4805	
D-321		1993	KSS331	CXA1571	CXD2515	CXP83916	MPC17A38	CXD2515		SM5853		LA4533	4mWx2, 16Ohm
D-231		1994	KSS331	BA6373	BU9310(w/DSP)	MSM65344	SC111281	RF5C241(ESP)		TC9293		BA3574	
D-335	350	1994	KSS331	CXA1782		CXP83412	SC1112801	CXD2508		TC9293		BA3574	
D-345 (D335 w/o digital-out)	200	1995											
D-777	450	1995	DAX01	BA6376		CXP83416	SC111284	BU9312	CXA8027	TC9404		LA4805	
D-E01/EJ01		1999	DAX21	CXD3027	TMP88CM22F	MPC17H17	CXD3027	MPC17A52	CXD3027	BUILT-IN		TA2120	
DENON													
DCP100	400	1989	KSS220	CXA1271	CXA1272	HD40L4808	MPC1715	CXD1246	CXD2551	PCM66*2	8xOversampling	M51568	
DCP50	250	1990	KSS220	CXA1081	CXA1082	CXP5086	TCA0372	CXD1167	SM5807	uPD6372	4xOversampling D.Filter	NJM2100+NJM3415(decent)	
DCP150	400	1991	KSS220	CXA1271	CXA1272	HD40L4808	MPC1715	CXD1167	SM5840	AD1868	dual 18-bit DAC, 8xOversampin	NJM3415	
DCP30	200	1992	KSS220	CXA1081	CXA1082	CXP5086	LA6536	CXD1167	PD00601	uPD6376	16-bit linear, 8fs digital filter	RC2100M+RC3415M	
DCP70	300	1992	KSS220	CXA1081	CXA1082	CXP5086	LA6536	CXD1167	PD00601	uPD6376	16-bit linear, 8fs digital filter	RC2100M+RC3415M	
DCP-7D		1993											
DCP-50/150 by Kaosun	350	2015	KSS220	CXA1081	CXA1082	CXP5086	TCA0372	CSD1167	SM5840	AD1868		NJM2100	20mW, 32Ohm
KENWOOD													
DPC-7 (developed w/Sony)		1987		CXA1081M	CXA1082	CXP5024	CXD1083	CXD1130		LC7880		NJM3415	20mWx2, 16Ohm
DPC-55		1988		(CX)A1081M	CXA1082	14D0408(Funai)	BA6280(CXA108)	CXD1130		LC7880		TA7415	
DPC-77	450	1988	KSS220	CXA1271	CXA1272	HD40L4804 (Hitachi)	MPC1715	CXD1167	SM5807	PCM60	4-fs digital filter	NJM3415	20mWx2, 16Ohm
DPC-81	300	1991	KSS220A	CXA1271	CSA1272	HD40L4804	MPC1715	CXD1167	PD00601	uPD6376		NJM3415	
DPC-61	249	1991	KSS220A	CXA1081	CXA1082			CXD1130		uPD6372	16-bit linear, 2xOversampling D	NJM3415+NJM2100	
CITIZEN													
CBM777			Sony SF (?86/90/91/P1?)	CXA1081	CXA1082	CXP5024	BA6920A (x2)	CXD1130		LC7880M		?NJM4558+NJM3415?	
CBM1000 [=Realistic CD-3100]	280	1988		(CX)A1081	CXA1082	CXP5024	CXA1083	CXD1130		LC7880M		NJM3415	
Seiko													
PHX-51CDX [-Sony D-33]			KSS220	CXA1081	CXA1082		AN8387	CXD1167		CXD1140		BA3570	
SANYO													
CP-10 (ac only) [=Siemens RW721 = Grundig CDP50]		1986		CX20108	CX20108	TMP47C420AF-I	MB3763	CX23035		CX20133	16 bit D/A converter// tr	NJM4556x2	
CP-12		1987											
HITACHI													
DA-P100 (ac only)	500	1986		CX20109	CX20108	MB88541PF-G-		CX23035		PCM55		NJM5532	
Technics/Panasonic													
SL-XP7		1985	SOAD10A	AN8370	AN8370	MN15845	AN6556	MN6617		PCM55		NJM4560	15mW, 32Ohm
SL-XP5	300	1986	FF-1	AN8370	AN8375	MN15845	AN8375	MN6617S		PCM55	16-bit linear, 7xOversmpl.D.Filte	SVIGA011x2+AN8376	30mW, 32Ohm
SL-NP10 (Panasonic)	280	1988		AN8370	AN8375	MN15845	AN8375	MN6617		PCM55		AN8376	30mW, 32Ohm
SL-XP2	250	1990	CD100	AN8373	AN8374	MN15845	AN8387	MN6625	SM5807	uPD6372	4xOversampling D.Filter	NJM2100	15mW, 16Ohm
PHILIPS													
CD10	370	1985	CDM2-P	TDA5708	TDA5709	TMP47C400F	L272x4	CXD23035		CX20133		NJM4560	30mWx2, 32Ohm
CD10MKII		1985	CDM2-P	TDA5708	TDA5709					PCM55		?	30mWx2, 32Ohm
D6800		1988	RCD-1C	M51567	M51564	TMP47C420	TDA7072	M50422		YM3016F		NJM3415	20mWx2, 32Ohm
AZ6808/19/29		1990	RCD3	M51567	M51564	TMP47C820F	MPC1715	SAA7341		SAA7341	1-bit DAC	NJM3416	
AZ6804/00/01/05/10/17	220	1990	RCD2/112A	M51567	M51564	TMP47C420	MPC1716	M50427		uPD6376	16-bit linear, 8fs digital filter	NJM3415	20mWx2, 32Ohm
AZ6897/00/01/05	300	1991	RCD2/11	M51567	M51564	TMP47C420	BA6280	M50422		YM3016		NJM4560x2+NJM3415x2(DBB)	20mWx2, 32Ohm
TOSHIBA													
P9/J9			DLAB-MK2	TA8101	TC9201	TMP47C420	TA8102	TC9200		TD6710		TA7415	
P20			DLAB-MK2	TA8101	TC9201	TMP47C420	BA6280	TC9200		TD6710		TA7415	
P21			DLAB-MK2	TA8101	TC9201	uPD75308	TA6270	TC9200		uPD6355		M51568	
P22			DLAB-MK2	TA8101	TC9221	uPD75308	uPD1725	TC9200		TC9219		TA8147	
XR-9458		1988	KSS220A (?)	TA8101	TC9201	uPD75308	TA6270	TC9200		uPD6355	16-bit D/A Converter	M51568	
XR-9421		1991	KSS220A	CXA1271	CXA1272	CXP5024	MPC1715	CXD1246		uPD6372	16-bit 2x oversampling	NJM3415	
Funai CDP-7600 = Tensai TPD-10 = Loewe CD100		1986	TOPH7820	TA8101	TC9201	TMP47C420	TA8102	TC9200		TD6710	14-BIT LINEAR	TA7415	-30mWx2, 32Ohm
FISHER													
Studio Standard PCD-100		1987		TA8101	TC9201	TMP47C420	CXA1083	TC9200	analog filter	TD6710	14-bits linear	TA7415	25mVx2
BSR (Birmingham Sound Reproducers)													
CCD-01 [by Toshiba]		1989	DLAB-MK2	TA8101	TC9201	TMP47C421	BA6280AF (x2)	TC9200		TD6710		TA7415	
JVC													
P70				TA9101	TC9200	TMP47C820	KA6104	TC9201	SM5818	uPD6376		M51568	
Optimus (RadioShack)													
CD-3200 [=Toshiba XR-9421]	220	1990											