

MODEL	MSRP(\$)	YEAR	OPT HEAD	RF AMP	SERVO	CPU	DRIVER	DSP	D. FILTER	DAC	DAC info (Sony/Vintage)	AUDIO AMP	HP output (per sv)
SONY													
D-5/D-50/D-14 (=Pioneer PD-C7)	300	1984	KSS110-I	CXA20109	CXA20108	MB88541	MB3876	CX23035		CX20133	16-bit linear, NO oversmp; Brick	NJM4560	10mWx2, 32Ohm
D-50mkII/D-7/D-77	300(batt+4)	1985	KSS110-II	CXA20108	CXA1023	CXP5024	CXA1083	CX23035		PCM55	16-bit linear	NJM4566	30mWx2, 32Ohm
D-700/D-170 (ac only)		1985	KSS110	CX20109	CX20108	CXP5034	NJM4558, Q551	CX23035		CX20133	16-bit linear	NJM4560	10mWx2, 32Ohm
CDP-7F (ac only)		1985	KSS121A	CX20109	CX20108	MSM6404	Q221//2/5/6	CX23035		CX20133	16-bit linear	NJM4560	10mWx2, 32Ohm
CDP-17F (ac only)		1987	KSS-160C	CXA1081	CXA1082	M50930	STA341M	CXD1130		LC7880		M5218	4.5mW, 32Ohm
CDP-S37/S207 (ac only)		1989	KSS-211A	CXA1081	CXA1082	MSC6458	CXA1291	CXD1125		CXD2550	4xOversampling Dual DAC	M5204P	11mWx2, 32Ohm
D-10/D-100	350(w/batt)	1986	KSS160A	CXA1081	CXA1082	CXP5086	CXA1083	CXD1125	SM5806S	PCM55	16-bit linear	NJM4566	30mWx2, 32Ohm
D-3/D-30		1987	KSS160A	CXA1081	CXA1082	UPD7503	CXA1083	CXD1125		CXD1140		M5216	15mWx2, 32Ohm
D-160/600		1988		CXA1081	CXA1082	CXP5024		CXD1130		LC7880	DAC w/D.Filter	M5216	15mWx2, 32Ohm
D-15/D-150	350	1988	KSS165	CXA1271	CXA1272	CXP5086	MPC1715	CXD1135		PCM60	16-bit linear	M51568	9mWx2, 32Ohm
D-2/D-20 (D-12 w/o MegaBass)	320	1988	KSS162//220	CXA1271	CXA1272	CXP5024	MPC1715	CXD1130		CXD1161	16-bit linear, 2fs digital filter	M51568	9mWx2, 32Ohm
D-4/D-40	320	1988	KSS162	CXA1271	CXA1272	CXP5024	MPC1715	CXD1130		CXD1161	16-bit linear, 2fs digital filter	M51568	9mWx2, 32Ohm
D-88	360	1988	KSS167	CXA1271	CXA1272	CXP5024	MPC1715	CXD1135		CXD1161	16-bit linear, 2fs digital filter	M51568	9mWx2, 32Ohm
D-25/D-250	360	1989	KSS160/221/225	CXA1271	CXA1272	CXP5086	MPC1715	CXD1125	CXD1316	PCM66	16-bit linear, 2fs digital filter	M51568	9mWx2, 32Ohm
D-35/D-350	400	1989	SF89 (Sanyo)	CXA1271	CXA1272	CXP5078	MPC1715	CXD1125	CXD2551	uPD6376	16-bit linear, 8fs digital filter	BA3570(w/DBB)	9mWx2, 16Ohm
D-555/D-Z555	500	1989	KSS167	CXA1271	CXA1272	CXP5086	MPC1715	CXD1125+CXD	CXD2550	PCM66 x2	16-bit linear, 8fs digital filter	2xNJM2107	9mWx2, 32Ohm
D-800K/D-180K	270	1989	KSS220A					CSD1246		CXD1161	16-bit linear, 2fs digital filter	NJM4560	9mWx2, 32Ohm
D-9/D-90	250	1989	KSS162//220	CXA1271	CXA1272	CXP5086	MPC1715	CXD1247		CXD1161	16-bit linear, 2fs digital filter	CXA1249(DBB)	9mWx2, 32Ohm
D-99		1990	KSS220	CXA1271	CXA1272	CXP5086	MPC1715	CXD1167		CXD8178	1-bit quartz time-axis control	BA3570(w/DBB)	5mWx2, 16Ohm
D-303v12	330	1990	SF89 (Sanyo)	CXA1271	CXA1272	CXP5078	MPC1716	CXD2500		CXD8178	1-bit quartz time-axis control	BA3570(w/DBB)	5mWx2, 16Ohm
D-303v14	330	1990	SF89 (Sanyo)	CXA1271	CXA1272	CXP5078	MPC1716	CXD2500	SM5840	SM5871	1-bit quartz time-axis control	BA3570(w/DBB)	9mWx2, 32Ohm
D-66	250	1990	SF89 (Sanyo)	CXA1271	CXA1272	CXP5086	MPC1715	CXD1125		uPD6376	DUAL DAC, 16-bit linear, 8fs dig	BA3570(w/DBB)	5mWx2, 16Ohm
D-11/12/22/T24		1990	KSS220	CXA1271	CXA1272	CXP5024	MPC1715	CXD1130/1245		CXD1161	16-bit linear, 2fs digital filter	BA3570(asDBB)	9mWx2, 32Ohm
D-202		1991	KSS330	CXA1271	CXA1272	CXP5086	MPC1716	CXD2500		uPD6376	16-bit linear, 8fs digital filter	BA3570(w/DBB)	5mWx2, 16Ohm
D-33		1991	KSS220	CXA1271	CXA1272	CXP5084	MPC1715	CXD1130	SM5840	uPD6376	16-bit linear, 8fs digital filter	BA3570(w/DBB)	5mWx2, 16Ohm
D-802K		1991	KSS220	CXA1271	CXA1602	CXP5084	MPC1715	CXD1167	SM5840	uPD6376	16-bit linear, 8fs digital filter	BA3570(w/DBB)	9mWx2, 32Ohm
D-808K		1991	KSS330	CXA1271	CXA1272	CXP5078	MPC1716	CXD2500	SM5840	PCM67	1-bit DAC	BA3570(w/DBB)	9mWx2, 16Ohm
D-J50		1991	KSS230	HA12156	CXA1272	S1400	MPC1716	CXD1167		PCM66	16-bit linear, 4fs digital filter	BA3558	5mWx2, 16Ohm
D-101		1991	KSS330	CXA1271	CXA1272	CXP5086	MPC1716	CXD2500		uPD6376	16-bit linear, 8fs digital filter	BA3570(w/DBB)	5mWx2, 16Ohm
D-211		1992	KSS330	CXA1271	CXA1602	UPD75328	MPC1716	CXD2500		SM5870		LA4534	9mWx2, 16Ohm
D-311		1992	KSS350	CXA1271	CXA1602	CXP5078	MPC1716	CXD2500		SM5870		LA4534	9mWx2, 16Ohm
D-515		1992	SF89 (Sanyo)	CXA1271	CXA1272	CXP50712	MPC1716	CXD2500		SM5870		LA4534	4mWx2, 16Ohm
D-34/36		1992	KSS220A	HA12168	HA12168	HD404818	MPC1715	HD49220	HD49220	HD49220	1-bit DAC	BA3570(w/DBB)	
D-822		1993	KSS331								1-bit DAC		
D121		1993	KSS331	CXA1672		CXP83412	SC11280	CXD2517		TC9276		LA4805	
D-321		1993	KSS331	CXA1571	CXD2515	CXP83916	MPC17A38	CXD2515		SM5853		LA4533	4mWx2, 16Ohm
D-231		1994	KSS331	BA6373	BU9310(w/DSP)	MSM65344	SC111281	RF5C241(ESP)		TC9293		BA3574	
D-335	350	1994	KSS331	CXA1782	CXA1782	CXP83412	SC1112801	CXD2508		TC9293		BA3574	
D-345 (D335 w/o digital-out)	200	1995											
D-777	450	1995	DAX-01A	BA6376		CXP83416	SC111284	BU9312	CXA8027	TC9404		LA4805	10mWx2, 16Ohm
D-E01/EJ01	350	1999	DAX21	CXD3027	TMP88CM22F	MPC17H17	CXD3027	MPC17A52	CXD3027	BUILT-IN		TA2120	
D-EJ985	250	2002	CDM-3325ER	CXD3039AR	CXD3039AR	T5AJ4-4H37	TB2130AF	CXD3039AR	CXD3039AR	CXD3039AR	1-bit	TA2152	5mWx2, 16Ohm
DENON													
DCP100	400	1989	KSS220	CXA1271	CXA1272	HD40L4808	MPC1715	CXD1246	CXD2551	PCM66*2	8xOversampling	M51568	
DCP50	250	1990	KSS220	CXA1081	CXA1082	CXP5086	TCA0372	CXD1167	SM5807	uPD6372	4xOversampling D.Filter	NJM3415	
DCP150	400	1991	KSS220	CXA1271	CXA1272	HD40L4808	MPC1715	CXD1167	SM5840	AD1868	dual 18-bit DAC, 8xOversamp	NJM3415	
DCP30	200	1992	KSS220	CXA1081	CXA1082	CXP5086	LA6536	CXD1167	PD00601	uPD6376	16-bit linear, 8fs digital filter	RC3415M	
DCP70	300	1992	KSS220	CXA1081	CXA1082	CXP5086	LA6536	CXD1167	PD00601	uPD6376	16-bit linear, 8fs digital filter	RC3415M	
DCP-50/150 by Kaosun	350	2015	KSS220	CXA1081	CXA1082	CXP5086	TCA0372	CSD1167	SM5840	AD1868		NJM2100	20mWx2, 32Ohm
KENWOOD													
DPC-7 (developed w/Sony)		1987		CXA1081M	CXA1082	CXP5024	CXD1083	CXD1130		LC7880		NJM3415	20mWx2, 16Ohm
DPC-55		1988		(CX)A1081M	CXA1082	14D0408(Funai)	BA6280(CXA108)	CXD1130		LC7880		TA7415	
DPC-77	450	1988	KSS162//220	CXA1271	CXA1272	HD40L4804 (Hitachi)		CXD1167	SM5807	PCM60	4-fs digital filter	NJM3415	20mWx2, 16Ohm
DPC-60		1989	KSS220A	CXA1081	CXA1082			CXD1130		uPD6372	16-bit linear, 2xOversampling D	NJM3415+NJM210	15mWx2, 16 Ohm
DPC-61	249	1991	KSS220A	CXA1081	CXA1082	CXP5086	TCA0372	CXD1130		uPD6372	16-bit linear, 2xOversampling D	NJM3415+NJM210	15mWx2, 16 Ohm
DPC-80		1989	KSS220A	CXA1081	CXA1082	HD404808	MPC1715	CXD1125	SM5814	PCM66		NJM3415+NJM341	20mWx2, 16Ohm
DPC-81	300	1990	KSS220A	CXA1271	CSA1272	HD40L4804	MPC1715	CXD1167	PD00601	uPD6376		NJM3415	
CITIZEN													
CBM777			Sanyo SF (?86/90/91/P1?)	CXA1081	CXA1082	CXP5024	BA6920A (x2)	CXD1130		LC7880M		?NJM4558+NJM3415?	
CBM1000 [=Realistic CD-3100, based on Ken	280	1988		(CX)A1081	CXA1082	CXP5024	CXA1083	CXD1130		LC7880M		NJM3415	
Seiko													
PHX-51CDX [-Sony D-33]			KSS220	CXA1081	CXA1082		AN8387	CXD1167		CXD1140		BA3570	
SANYO													
CP-10 (ac only) [=Siemens RW721 = Grundig CDP50]		1986		CX20108	CX20108	TMP47C420AF-I	MB3763	CX23035		CX20133	16 bit D/A converter// tr	NJM4556x2	
CP-12		1987		CXA1081	CXA1082	CXP5024	BA6280	CXD1130		LC7880M		NJM4556	30mWx2, 32Ohm
HITACHI													
DA-P100	500	1986		CX20109	CX20108	MB88541PF-G-		CX23035		PCM55		NJM5532	
Technics/Panasonic													
SL-XP7 (=SL-XP3//SL-NP3)		1985	SOAD10A	AN8370	AN8370	MN15845	AN6556	MN6617		PCM55		NJM4560	15mW, 32Ohm
SL-XP6//SL-NP10 (Panasonic, 1988, \$280) = C	300	1986	FF-1	AN8370	AN8375	MN15845	AN8375	MN6617S	MN6618	PCM55	16-bit linear, ?xOversamp	AN8376	30mW, 32Ohm
SL-XP6 = SL-NP11=SL-XP50	280	1989	SOAD100A	AN8373	AN8374	MN15845	AN8385	MN6617	SM5807	PCM60	4xOversampling D.Filter	NJM2100	15mW, 32Ohm
SL-NP12		1990	SODD100Z	AN8373	AN8374	MN15845	AN8387	MN6625	SM5807	uPD6372	4xOversampling D.Filter	NJM3414	15mW, 16Ohm
SL-XP2	250	1990	SODD100Z(=CD100)	AN8373	AN8374	MN15845	AN8387	MN6625	SM5807	uPD6372	4xOversampling D.Filter	NJM3414	15mW, 16Ohm
SL-XP1 = SL-NP1		1991	SODD100Z	AN8373	AN8374	MN15845	AN8387	MN6625	SM5807	uPD6376	4xOversampling D.Filter	NJM3415	15mW, 16Ohm
SL-XP300		1991	SODD100Z	AN8373	AN8374	UPD75308	AN8387	MN6625	SM5840	uPD6376	8x 18bit oversampling	NJM3415	15mW, 16Ohm
AKAI PD-X52			SF-92.5 (Sanyo)	TA8191			TMP47C420	AN8387 (x2)	TC9236			BA3570(w/DBB)	
PHILIPS													
CD10	370	1985	CDM2-P	TDA5708	TDA5709	TMP47C400F	L272x4	CXD23035		CX20133		NJM4560	30mWx2, 32Ohm
CD10MKII		1985	CDM2-P	TDA5708	TDA5709	TMP47C420AF-8353				PCM55		?	30mWx2, 32Ohm
D6800		1988	RCD-1C	M51567	M51564	TMP47C420AF-I	TDA7072	M50422		YM3016F		NJM3415	20mWx2, 32Ohm
AZ6808		1990	RCD3	M51567	M51564	TMP47C820F	MPC1715	SAA7341		SAA7341	1-bit DAC	NJM3415	20mWx2, 32Ohm
AZ6804//6806//6817	220	1990	RCD2//112A	M51567	M51564	TMP47C420	MPC1716	MN6625		uPD6376	4xOversampling 16-bit linear, 8fs	NJM3415	20mWx2, 32Ohm
AZ6892//6893//6897	300	1991	RCD2//11	M51567	M51564	TMP47C420	BA6280	M50422		M3016		NJM3415(DBB)	20mWx2, 32Ohm
AZ6811//6812//6813		1991	RCD2	M51567	M51564	COP472-3	MPC1715					NJM3415	20mWx2, 32Ohm
CROWN													
CD-110/220		198											